



## DIGITRADIO 100

Portable Digital radio for DAB+, DAB and FM reception

EAN	Item no.	Weight (Box)	Device (W x H x D)	Weight	Colour	Box
4019588049574	0000/4957	518 g	13.00 x 10.00 x 5.00 cm	196 g	black	20.00 x 16.50 x 5.50 cm

<b>BLUETOOTH VERSION &amp; PROFILE</b> Bluetooth version: 2.1 + EDR AVRCP (Audio Video Remote Control Profile): Ja A2DP (Advanced Audio Distribution Profile): Ja	<b>KEY FEATURES</b> DAB+: Yes FM / RDS: Yes Clock: Yes Alarm / sleep timer: Yes	Standby: 0,44 W <b>POWER SUPPLY</b> Nominal voltage: 230 V Frequency: 50 Hz Mains adapter: DC 6 V / 500 mA Type of power supply: external
<b>CONNECTIONS</b> Audio out analogue (3,5mm): 1 connector external antenna: 1	<b>KEY FEATURES</b> DAB+: Yes FM / RDS: Yes Clock: Yes Alarm / sleep timer: Yes	<b>RADIO / RECEPTION</b> DAB+: 174 - 240 MHz FM/RDS: 87.5 - 108 MHz Aerial: DAB/FM aerial
<b>DISPLAY</b> Size: 2.8 Zoll Dimmable: Yes Type: LCD	<b>KEY FEATURES</b> DAB+: Yes FM / RDS: Yes Clock: Yes Alarm / sleep timer: Yes	<b>RADIO TYPE</b> radio adapter: Yes stationary radio: Yes
<b>ENVIRONMENT</b> Humidity: 5 - 90 % relative Luftfeuchtigkeit (nicht kondensierend) Ambient temperature: 5 - 35 °C	<b>OTHER FEATURES</b> OSD languages: German, English, French, Italian	<b>STREAMING</b> Bluetooth audio streaming: Yes
<b>HANDLING/COMFORT</b> Alarm: Yes Sleep timer: Yes Snooze: Yes Favourites programme manager FM: 12	<b>POWER CONSUMPTION</b> In operation: 3 W	<b>SCOPE OF DELIVERY</b> DigitRadio 100, FM/DAB antenna, audio connector cable, plug-in power supply, remote control, instruction manual

KEYFEATURES		
Clock	Alarm / sleep timer	FM / RDS
Bluetooth Audio Streaming	DAB+	